



# Load-Pickup Tool Sets - 15kV, 12' #2 Cable

by CHANCE Utility  
Catalog ID: C4031558



15kV Load-Pickup Tool, 12' of #2 cable, main line range of 0.162" to 1.108". Each completely assembled set consists of Load-Pickup Tool, Jumper Clamp, 15kV Jumper Cable and cable connectors.

- Rated for loads as high as 250 amperes
- Rated to pick up and carry 250-amp loads at 15kV
- Each completely assembled set consists of Load-Pickup Tool, Jumper Clamp, 15 kV Jumper Cable and cable connectors
- Load-Pickup Tool and Jumper Clamp fit conductors from #6 Copper (0.162") through 795 kcmil (1.108")
- Handguard of high-impact Nylon keeps hand away from energized area
- Four standard sets include options for 10' or 12' lengths of either #2 or 1/0 Jumper Cable
- Other custom pre-assembled sets are available
- Individual components also may be ordered for customer assembly of various combinations

\* Representative image

## Product Details

### General

Style	Complete Set
UPC	096359019152

### Dimensions

Weight	18.62 lb
--------	----------

### Electrical Ratings

Current Rating	200 A
----------------	-------

### Conductor Related

Conductor Diameter (Main) - Maximum	1.108 in
Conductor Diameter (Main) - Minimum	0.162 in
Conductor Size	#2 AWG

**For further technical assistance, please contact us**

#### Domestic Customer Service

Hubbell Power Systems  
210 N. Allen Centralia, MO 65240 USA  
Phone: (573) 682-5521  
Fax: (573) 682-8475  
Email: [hpscsc@hubbell.com](mailto:hpscsc@hubbell.com)

#### International Customer Service

Phone: +1-573-682-5521  
Fax: +1-573-682-8516  
Email: [hpsintlcs@hubbell.com](mailto:hpsintlcs@hubbell.com)